



Z-Wave Protocol Implementation Conformance Statement

Plug-in Dual Smart Switch, Independant Control With USB Charging

General Information

Product Identifier: 28177/ZW4105
Brand Name: GE
Product Version: HW: 255 FW: 5.23
Z-Wave Certification #: ZC10-17105795

Product Features

Loads Controlled 2
Firmware Updatable Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x3132
Z-Wave Product Type: 0x5052
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.51.10
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Group 2 supports Basic Set and is controlled with the local load

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Plug-in Dual Smart Switch, Independant Control With USB Charging

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic