

## Z-Wave Protocol Implementation Conformance Statement

### Danalock V3-BTZH-ANZ

#### General Information

<b>Product Identifier:</b>	Danalock V3-BTZH-ANZ
<b>Brand Name:</b>	Danalock
<b>Product Version:</b>	HW: 2 FW: 1.02:00.07
<b>Z-Wave Certification #:</b>	ZC10-17105802

#### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	CR123
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	Access Control

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0009
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Danalock V3-BTZH-ANZ

### Supported Command Classes (16):

Association Group Info  
Battery  
Device Reset Locally  
Firmware Update Meta-Data V4  
Notification V8  
Security S0  
Supervision  
Version V2

Association V2  
Configuration  
Door Lock V2  
Manufacturer Specific V2  
Powerlevel  
Security S2  
Transport Service V2  
Z-Wave Plus Info V2