

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Garage Door Controller

General Information

Product Identifier:	GD00Z-7
Brand Name:	GoControl
Product Version:	HW: 3 FW: 0.89:00.27
Z-Wave Certification #:	ZC10-17115876

Product Features

Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Access Control
Color	Black

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3531
Z-Wave Product Type:	0x4744
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Barrier Operator / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Garage Door Controller

Supported Command Classes (15):

Application Status	Association Group Info
Association V2	Barrier Operator
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V8
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	