

## Z-Wave Protocol Implementation Conformance Statement

### DKC1001

#### General Information

<b>Product Identifier:</b>	DKC1001
<b>Brand Name:</b>	Enblink
<b>Product Version:</b>	HW: 1 FW: 4.62:01.05
<b>Z-Wave Certification #:</b>	ZC10-17105815

#### Product Features

**Firmware Updatable** Updatable by Manufacturer

**Communications Connections** Ethernet (Wired)  
Ethernet (Wireless/WiFi)  
USB (Universal Serial Bus)

**Sensors** Acceleration X-Axis  
Acceleration Y-Axis  
Acceleration Z-Axis  
Air Flow  
Air Temperature  
Atmospheric Pressure  
Barometric Pressure  
Basic Metabolic Rate  
Blood Pressure  
Body Mass Index  
Bone Mass  
Carbon Dioxide  
Carbon Monoxide  
Current  
Dew Point  
Direction  
Distance  
Electrical Conductivity  
Electrical Resistivity  
Fat Mass  
Formaldehyde CH<sub>2</sub>O Level  
Freeze

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

DKC1001

## Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	South Korea
<b>Z-Wave Product ID:</b>	0x0004
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.01
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Central Controller / Central Static Controller

## Association Group Information

**Group # / Max**    **Description**

### Nodes

1 / 5                    Z-Wave Plus Lifeline

### Supported Command Classes (10):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (17):

Association Group Info	Association V2
Basic	Battery
CRC16 Encapsulation	Door Lock V3
Manufacturer Specific	Meter V4
Multi-Channel Association V3	Multi-Channel V4
Security S0	Sensor Multilevel V10
Switch Binary V2	Switch Multilevel V4
Version V2	Wake Up V2
Z-Wave Plus Info V2	