

Z-Wave Protocol Implementation Conformance Statement

KOMFORTHHAUS Spirit Z-Wave Plus

General Information

Product Identifier:	4250848804063
Brand Name:	KOMFORTHHAUS
Product Version:	HW: 49 FW: 0.16:00.10
Z-Wave Certification #:	ZC10-17115875

Product Features

Battery Type	LR06
Battery Quantity	2
Firmware Updatable	Updatable by Consumer by RF
Thermostat Modes	Energy Save Heat Heat
Sensors	Air Temperature
Thermostat HVAC Systems Supported	Heat Only
Supported Notification Types	Power Management System

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

KOMFORTH AUS Spirit Z-Wave Plus

Z-Wave Technical Information

Z-Wave Frequency:	UAE
Z-Wave Product ID:	0x0003
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Thermostat - HVAC / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1 Z-Wave Plus Lifeline

Supported Command Classes (21):

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific
Notification V8	Powerlevel
Protection	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Multilevel
Thermostat Mode V3	Thermostat Setpoint V3
Transport Service V2	Version V2
Z-Wave Plus Info V2	