

Z-Wave Protocol Implementation Conformance Statement

ON/OFF PLUG

General Information

Product Identifier:	AN186-1
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.00:00.05
Z-Wave Certification #:	ZC10-17115857

Product Features

Color	White
Switch Load Capacity Watts	1400
Supported Notification Types	Power Management
Switch Load Capacity Current	12
Switch Load Capacity Volt-Ampere	120
Communications Connections	None
Electric Load Type	Incandescent LED
Sensors	Power

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ON/OFF PLUG

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x000C
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Association with 1 node.
2 / 4	Association with 4 nodes (i.e. end devices such as detectors or other lighting switches). This allows the On/Off module to receive commands directly from these end devices without the participation of the controller.

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific	Notification V4
Powerlevel	Security S0
Security S2	Supervision
Switch All	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic