

## Z-Wave Protocol Implementation Conformance Statement

### S100 Socket iO

#### General Information

<b>Product Identifier:</b>	10002041-13X
<b>Brand Name:</b>	Simon
<b>Product Version:</b>	HW: 1 FW: 4.24:68.49
<b>Z-Wave Certification #:</b>	ZC10-18026012

#### Product Features

<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>Switch Load Capacity Current</b>	16
<b>Neutral Wire Required</b>	Yes
<b>Supported Meter Type</b>	Electric Energy
<b>Switch Type</b>	Toggle

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0000
<b>Z-Wave Product Type:</b>	0x0009
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

S100 Socket iO

## Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 3                    Z-Wave Plus Lifeline Reports Meter Watts consumption when load consumption changes more than 10%.  
Report Basic commands when load state changes.

**Supported Command Classes (12):**

Association Group Information V3	Association V2
Basic	Configuration V2
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V4
Powerlevel	Switch Binary
Version V2	Z-Wave Plus Info V2