

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Wall Dimmer with RGB LED

General Information

Product Identifier:	HS-WD200+
Brand Name:	HomeSeer
Product Version:	HW: 255 FW: 5.08
Z-Wave Certification #:	ZC10-18026019

Product Features

Neutral Wire Required	Yes
Outdoor Use	No
Z-Wave Scene Type	Scene & Central Scene
Electric Load Type	Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) Incandescent
Color	White
Switch Type	Decorator Paddle Rocker
Switch Load Capacity Watts	600 Watts Incandescent
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Wall Dimmer with RGB LED

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3036
Z-Wave Product Type:	0x4447
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch All
Switch Multilevel V4	Transport Service V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Central Scene V3	Supervision
------------------	-------------