

Z-Wave Protocol Implementation Conformance Statement

In-wall Smart Dimmer

General Information

Product Identifier:	NZW31T
Brand Name:	Inovelli
Product Version:	HW: 1 FW: 20.15
Z-Wave Certification #:	ZC10-17115841

Product Features

Neutral Wire Required	Yes
Outdoor Use	No
Switch Type	Toggle
Z-Wave Scene Type	Central Scene
Color	White
Switch Load Capacity Watts	600

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x261C
Z-Wave Product Type:	0x0111
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Routing Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-wall Smart Dimmer

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (10):

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Switch All	Switch Multilevel
Version V2	Z-Wave Plus Info V2