



### **Z-Wave Protocol Implementation Conformance Statement**

# Zipato Bulb 2

#### **General Information**

Product Identifier:	rgbw2.us
Brand Name:	Zipato
Product Version:	HW: 0 FW: 2.26
Z-Wave Certification #:	ZC10-17115889

#### **Product Features**

#### Firmware Updatable

Updatable by Consumer by RF

Color

White

#### **Z-Wave Product Information**

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### **Z-Wave Technical Information**

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0006
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

#### **Association Group Information**

Group # / Max	Description
Nodes	
1 / 1	Z-Wave Plus Lifeline

## Z-Wave Protocol Implementation Conformance Statement (Continued) Zipato Bulb 2

#### Supported Command Classes (15):

Association Group Info Basic Device Reset Locally Manufacturer Specific V2 Security S0 Switch Color Switch Multilevel V2 Z-Wave Plus Info V2 Association V2 Configuration V2 Firmware Update Meta-Data V2 Powerlevel Switch All Switch Multilevel Version V2