

Z-Wave Protocol Implementation Conformance Statement

In-Wall Fan Control

General Information

Product Identifier: 39358 / ZW4002
Brand Name: Honeywell
Product Version: HW: 255 FW: 5.23
Z-Wave Certification #: ZC10-17125903

Product Features

Switch Load Capacity Current 2.5
Neutral Wire Required Yes
Firmware Updatable Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x3131
Z-Wave Product Type: 0x4944
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.51.10
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Fan Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Fan Control

- 2 / 5 Supports Basic Set and is controlled with the local load
- 3 / 5 Supports Basic Set and is controlled by double pressing the On or Off button

Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Multilevel	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic