

Z-Wave Protocol Implementation Conformance Statement

In-Wall Tamper Resistant Smart Outlet

General Information

Product Identifier:	14288/ZW1002
Brand Name:	GE
Product Version:	HW: 255 FW: 5.24
Z-Wave Certification #:	ZC10-18025987

Product Features

Firmware Updatable	Updatable by Consumer by RF
---------------------------	-----------------------------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3133
Z-Wave Product Type:	0x4952
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Supports Basic Set and is controlled with the local load
3 / 5	Supports Basic Set and is controlled by pressing the On or Off button

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Tamper Resistant Smart Outlet

Supported Command Classes (15):

Association Group Info
Basic
CRC16 Encapsulation
Firmware Update Meta-Data V2
Powerlevel
Scene Actuator Conf
Switch Binary
Z-Wave Plus Info V2

Association V2
Configuration
Device Reset Locally
Manufacturer Specific V2
Scene Activation
Switch All
Version V2

Controlled Command Classes (1):

Basic