

Z-Wave Protocol Implementation Conformance Statement

ON/OFF PLUG

General Information

Product Identifier:	AN186-F
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.01:00.01
Z-Wave Certification #:	ZC10-18015960

Product Features

Switch Load Capacity Volt-Ampere	100
Switch Load Capacity Watts	1200
Supported Notification Types	Power Management
Electric Load Type	Incandescent LED
Color	White
Firmware Updatable	Updatable by Consumer via Internet
Switch Load Capacity Current	12

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ON/OFF PLUG

Z-Wave Technical Information

Z-Wave Frequency:	Japan
Z-Wave Product ID:	0x000C
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Association with 1 node.
2 / 4	Association with 4 nodes (i.e. end devices such as detectors or other lighting switches). This allows the On/Off module to receive commands directly from these end devices without the participation of the controller.

Supported Command Classes (16):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific	Notification V4
Powerlevel	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic