



# Z-Wave Protocol Implementation Conformance Statement

## Door Sensor

### General Information

**Product Identifier:** ZD2105US-5  
**Brand Name:** Raylios  
**Product Version:** HW: 1 FW: 5.01:10.02  
**Z-Wave Certification #:** ZC10-18015978

### Product Features

**Supported Notification Types** Home Security

### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
 Supports Z-Wave Network Security? Yes  
 Supports Z-Wave AES-128 Security S0? Yes  
 Supports Security S2? No  
 SmartStart Compatible? No

### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x2201  
**Z-Wave Product Type:** 0x2022  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.51.06  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Notification Sensor / Reporting Sleeping Slave

### Association Group Information

**Group # / Max Description**

#### Nodes

1 / 5 Z-Wave Plus Lifeline \* Support grouping identifier=1, one group with 5 nodes, \* Association is used for other grouping devices chain reaction. \* All triggering reports & low voltage report will be sent to the associated nodes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door Sensor

### Supported Command Classes (12):

Command Class Association Group Info  
Command Class Battery  
Command Class Firmware Update Md V2  
Command Class Notification V4  
Command Class Security  
Command Class Wake Up V2

Command Class Association V2  
Command Class Device Reset Locally  
Command Class Manufacturer Specific V2  
Command Class Powerlevel  
Command Class Version V2  
Command Class Z-Wave+ Info V2

### Controlled Command Classes (1):

Command Class Basic