

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Plug-In On/Off Switch

General Information

Product Identifier:	PA-100
Brand Name:	ZLINK
Product Version:	HW: 255 FW: 50.03
Z-Wave Certification #:	ZC10-18025998

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF
Outdoor Use	No
Electric Load Type	Fluorescent Incandescent LED
Switch Load Capacity Volt-Ampere	120VAC
Switch Load Capacity Current	15Amps
Switch Type	Push Button Illuminated
Switch Load Capacity Watts	1800W resistive load

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plug-In On/Off Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3031
Z-Wave Product Type:	0x4447
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1 1. Z-Wave Plus Lifeline 2. Device Reset Locally Notification

Supported Command Classes (16):

Association Group Info	Association V2
Basic	Configuration V3
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Supervision