

Z-Wave Protocol Implementation Conformance Statement

Multi-Channel Remote Control

General Information

Product Identifier:	MCZ1
Brand Name:	Bali
Product Version:	HW: 255 FW: 11.14
Z-Wave Certification #:	ZC10-18066153

Product Features

Firmware Updatable	Not Updatable
Switch Load Capacity Watts	.15
Switch Type	Push Button with Indicator
Window Covering Control Features	Endpoint Aware
Switch Load Capacity Current	.05
Z-Wave Scene Type	Central Scene
Battery Type	AAA Battery
Color	White
Battery Quantity	2

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Multi-Channel Remote Control

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x5A31
Z-Wave Product Type:	0x4D43
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Portable Controller
Z-Wave Device Type / Role Type:	Remote Control - Simple / Portable Controller

Association Group Information

Group # / Max Description

Nodes

1 / 1	Z-Wave Plus Lifeline (Primary) Battery Status CC Device Reset Locally CC Central Scene CC
2 / 12	Slave Shade Group (12 Nodes Max) CC MultiLevel Switch

Supported Command Classes (12):

Association Group Info	Association V2
Basic	Battery
Central Scene V3	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Version V2
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (2):

Central Scene V3	Switch Multilevel
------------------	-------------------