



Z-Wave Protocol Implementation Conformance Statement

Z-Wave Metering Plug Smart Start

General Information

Product Identifier:	POPE700397
Brand Name:	Popp & Co.
Product Version:	HW: 1 FW: 3.01
Z-Wave Certification #:	ZC10-18026015

Product Features

Sensors	Voltage
Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED
Outdoor Use	Yes
Switch Load Capacity Watts	3500
Supported Meter Type	Electric Energy
IP (Ingress Protection) Rated	Yes
Firmware Updatable	Updatable by Consumer by RF
Color	White

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Metering Plug Smart Start

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x000A
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 5	Control other devices on single click of the button. BASIC command (on/off) is sent according to switching state of the load.

Supported Command Classes (19):

Command Class Association Group Info	Command Class Association V2
Command Class Basic	Command Class Central Scene V3
Command Class Configuration	Command Class Device Reset Locally
Command Class Firmware Update Md V4	Command Class Manufacturer Specific V2
Command Class Meter V4	Command Class Multi Channel Association V3
Command Class Powerlevel	Command Class Protection
Command Class Security 2	Command Class Sensor Multilevel V8
Command Class Supervision	Command Class Switch Binary
Command Class Transport Service V2	Command Class Version V3
Command Class Z-Wave+ Info V2	

Controlled Command Classes (1):

Command Class Basic
