

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Plus Smart Switch - Double Toggle

General Information

Product Identifier:	DTLS2-ZWAVE5
Brand Name:	Ecolink Intelligent Technology
Product Version:	HW: 255 FW: 10.01
Z-Wave Certification #:	ZC10-18026030

Product Features

Battery Quantity	2
Battery Type	AA
Color	White
Sensors	Open/Closed (Binary)
Switch Type	Toggle

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0004
Z-Wave Product Type:	0x0006
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Listening Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plus Smart Switch - Double Toggle

Association Group Information

Group # / Max Description

Nodes

- 1 / 1 Group one is the lifeline group. The Light Switch will send Switch Binary Reports with a value of 0x00 if the light is turned off and 0xFF if the light is turned on to all nodes in group 2.
- 2 / 1 Group two – The light switch will send basic reports with a value of 0x00 if the light is turned off and 0xFF if the light is turned on to all nodes in group 2.

Supported Command Classes (10):

Association Group Info	Association V2
Basic	Battery
Device Reset Locally	Manufacturer Specific
Powerlevel	Switch Binary
Version V2	Z-Wave Plus Info V2