

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Wall Dimmer

General Information

Product Identifier:	HS-WD100+
Brand Name:	HomeSeer
Product Version:	HW: 255 FW: 50.03
Z-Wave Certification #:	ZC10-18036076

Product Features

Color	White
Electric Load Type	Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) Incandescent
Switch Load Capacity Watts	600 Watts Incandescent
Neutral Wire Required	Yes
Outdoor Use	No
Switch Type	Decorator Paddle Rocker
Z-Wave Scene Type	Scene & Central Scene
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Wall Dimmer

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3034
Z-Wave Product Type:	0x4447
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Central Scene V3	Supervision
------------------	-------------