

## Z-Wave Protocol Implementation Conformance Statement

# Direct-Wire Outdoor Smart Switch (40 Amp)

### General Information

<b>Product Identifier:</b>	14285/ZW4007
<b>Brand Name:</b>	GE
<b>Product Version:</b>	HW: 255 FW: 5.53
<b>Z-Wave Certification #:</b>	ZC10-18056123

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	40
<b>Loads Controlled</b>	2
<b>Outdoor Use</b>	Yes
<b>Supported Meter Type</b>	Electric Energy
<b>Z-Wave Scene Type</b>	Scene & Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3032
<b>Z-Wave Product Type:</b>	0x4F44
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Direct-Wire Outdoor Smart Switch (40 Amp)

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

- 1 / 5                Z-Wave Plus Lifeline, Binary Switch Report
- 2 / 5                Basic Set, controlled by local load
- 3 / 5                Basic Set, controlled by pressing the On or Off button

**Supported Command Classes (18):**

- |                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Basic                        | Central Scene V3         |
| Configuration V3             | Device Reset Locally     |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Meter V3                     | Powerlevel               |
| Scene Activation             | Scene Actuator Conf      |
| Security S2                  | Supervision              |
| Switch Binary                | Transport Service V2     |
| Version V2                   | Z-Wave Plus Info V2      |

**Controlled Command Classes (1):**

- Basic