

## Z-Wave Protocol Implementation Conformance Statement

### SmartThings Wifi

#### General Information

<b>Product Identifier:</b>	ET-WV525
<b>Brand Name:</b>	Samsung Electronics, Co., Ltd.
<b>Product Version:</b>	HW: 36 FW: 4.38:00.17
<b>Z-Wave Certification #:</b>	ZC10-18076172

#### Product Features

<b>Controller Supports Multiple Networks</b>	No
<b>Gateway Has Preferred Partners</b>	Yes
<b>Controller Supports Multiple Z-Wave Interfaces</b>	No
<b>Communications Connections</b>	Ethernet (Wired)
<b>Supported Notification Types</b>	Smoke Alarm Water Alarm
<b>Z-Wave Scene Type</b>	Central Scene
<b>Firmware Updatable</b>	Updatable by Consumer by Wire
<b>Color</b>	White
<b>Sensors</b>	Air Temperature Humidity Luminance

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

SmartThings Wifi

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0024
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	SD3503
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Central Controller / Central Static Controller

## Association Group Information

**Group # / Max    Description**

### Nodes

1 / 4                Z-Wave Plus Lifeline

### Supported Command Classes (11):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
No Operation	Powerlevel
Security S0	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (28):

Association Group Info	Association V2
Barrier Operator	Basic
Battery	Configuration V2
CRC16 Encapsulation	Device Reset Locally
Door Lock V2	Manufacturer Specific V2
Meter V3	Multi-Channel Association V3
Multi-Channel V4	Notification V5
Security S0	Sensor Binary V2
Sensor Multilevel V5	Switch Binary
Switch Color V2	Switch Multilevel V3
Thermostat Fan Mode V3	Thermostat Fan State V2
Thermostat Mode V2	Thermostat Operating State V2
Thermostat Setpoint V2	Version V2
Wake Up V2	Z-Wave Plus Info V2