

Z-Wave Protocol Implementation Conformance Statement

Z-Wave RGB Fan Controller

General Information

Product Identifier:	HS-FC200+
Brand Name:	HomeSeer
Product Version:	HW: 255 FW: 50.01
Z-Wave Certification #:	ZC10-18066137

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	2.5 Amps
Switch Load Capacity Volt-Ampere	120 VAC
Switch Load Capacity Watts	300 Watts
Neutral Wire Required	Yes
Outdoor Use	No
Switch Type	Decorator Paddle Rocker
Z-Wave Scene Type	Scene & Central Scene
Electric Load Type	Inductive (e.g. Motor)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave RGB Fan Controller

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0203
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Fan Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Central Scene V3	Supervision
------------------	-------------