

## Z-Wave Protocol Implementation Conformance Statement

### Control Center Gateway

#### General Information

<b>Product Identifier:</b>	PSC03
<b>Brand Name:</b>	Philio Technology
<b>Product Version:</b>	HW: 1 FW: 6.01:02.81:08.12
<b>Z-Wave Certification #:</b>	ZC10-18106288

#### Product Features

<b>Communications Connections</b>	Ethernet (Wireless/WiFi)
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Supported Notification Types</b>	Access Control Home Security Smoke Alarm Water Alarm
<b>Sensors</b>	Air Temperature Humidity Luminance Motion/No Motion (Binary) Open/Closed (Binary)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Control Center Gateway

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0054
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	SD3503
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                Z-Wave Plus Lifeline

**Supported Command Classes (13):**

Association Group Information V3	Association V2
CRC16 Encapsulation	Device Reset Locally
Inclusion Controller	Manufacturer Specific V2
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (17):**

Association Group Information V3	Association V2
Basic	Battery
CRC16 Encapsulation	Manufacturer Specific V2
Meter	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Security S0	Security S2
Sensor Multilevel V5	Switch Binary
Version V2	Wake Up V2
Z-Wave Plus Info V2	