

Z-Wave Protocol Implementation Conformance Statement

Smart Door Sensor

General Information

Product Identifier:	HS3DS-Z
Brand Name:	HEIMAN
Product Version:	HW: 255 FW: 3.01
Z-Wave Certification #:	ZC10-18106248

Product Features

Battery Type	CR2
Color	White
Communications Protocol	Z-Wave Serial API
Supported Notification Types	Access Control Emergency Alarm Home Security Irrigation
Battery Quantity	1PC

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0168
Z-Wave Product Type:	0x0168
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.03

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Door Sensor

Association Group Information

Group # / Max Description

Nodes

1 / 5 Lifeline association group
2 / 5 Root Device group(Basic set)

Supported Command Classes (14):

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2