

Z-Wave Protocol Implementation Conformance Statement

Smart Plug

General Information

Product Identifier:	HKZW-SO09(P)
Brand Name:	Hank
Product Version:	HW: 1 FW: 1.01
Z-Wave Certification #:	ZC10-19016347

Product Features

Firmware Updatable	Updatable by Consumer via Internet
Supported Meter Type	Electric Energy
Switch Load Capacity Current	10A
Switch Load Capacity Volt-Ampere	120V
Switch Load Capacity Watts	1200W
Color	White
Switch Type	Push Button Illuminated
Communications Protocol	Z-Wave Serial API
Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x001B
Z-Wave Product Type:	0x0101
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2