

## Z-Wave Protocol Implementation Conformance Statement

# Schlage Connect Smart Deadbolt

### General Information

<b>Product Identifier:</b>	BE468ZP
<b>Brand Name:</b>	Schlage
<b>Product Version:</b>	HW: 3 FW: 3.03:10.09
<b>Z-Wave Certification #:</b>	ZC10-18106259

### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	AA
<b>Door Lock Type</b>	Deadbolt
<b>Supported Notification Types</b>	Access Control Power Management System

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0468
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.02
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Schlage Connect Smart Deadbolt

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 2                    Z-Wave Lifeline

**Supported Command Classes (21):**

Anti-Theft V2	Association Group Info
Association V2	Basic
Battery	Configuration
Device Reset Locally	Door Lock V2
Firmware Update Meta-Data V3	Manufacturer Specific
Notification V8	Powerlevel
Schedule Entry Lock V3	Security S0
Security S2	Supervision
Time	Transport Service V2
User Code	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Time