

Z-Wave Protocol Implementation Conformance Statement

Samsung SmartThings Hub (2018)

General Information

Product Identifier:	IM6001-V3P01
Brand Name:	SmartThings
Product Version:	HW: 32 FW: 5.03:00.22
Z-Wave Certification #:	ZC10-18086209

Product Features

Color	White
Communications Connections	Bluetooth Ethernet (Wired) Ethernet (Wireless/WiFi) USB (Universal Serial Bus)
Communications Protocol	Z-Wave Serial API
Firmware Updatable	Updatable by Manufacturer
Sensors	Air Temperature Humidity Luminance
Supported Notification Types	CO Alarm Home Security Smoke Alarm Water Alarm

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Samsung SmartThings Hub (2018)

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0020
Z-Wave Product Type:	0x0007
Z-Wave Hardware Platform:	SD3503
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Static Controller
Z-Wave Device Type / Role Type:	Central Controller / Central Static Controller

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (11):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
No Operation	Powerlevel
Security S0	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (30):

Association Group Info	Association V2
Barrier Operator	Basic
Battery	Clock
Configuration V2	CRC16 Encapsulation
Device Reset Locally	Door Lock V2
Manufacturer Specific V2	Meter V3
Multi-Channel Association V3	Multi-Channel V4
Notification V5	Security S0
Sensor Binary V2	Sensor Multilevel V5
Switch Binary	Switch Color V2
Switch Multilevel V3	Thermostat Fan Mode V3
Thermostat Mode V2	Thermostat Operating State V2
Thermostat Setpoint V2	User Code
Version V2	Wake Up V2
Window Covering	Z-Wave Plus Info V2