



## Z-Wave Protocol Implementation Conformance Statement

# Eaton's Z-Wave Plus Wireless Switch

### General Information

<b>Product Identifier:</b>	RF9601
<b>Brand Name:</b>	Eaton
<b>Product Version:</b>	HW: 255 FW: 2.00
<b>Z-Wave Certification #:</b>	ZC10-18096234

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	15A
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Decorator Paddle Push with Indicator
<b>Z-Wave Scene Type</b>	Scene
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Eaton's Z-Wave Plus Wireless Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0503
<b>Z-Wave Product Type:</b>	0x534C
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave, No FLiRS, No MR
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5	Z-Wave Plus Lifeline
2 / 5	ON/OFF

**Supported Command Classes (19):**

Command Class Alarm	Command Class Association Group Info
Command Class Association V2	Command Class Basic V2
Command Class Configuration	Command Class Device Reset Locally
Command Class Firmware Update Md V2	Command Class Manufacturer Specific V2
Command Class Node Naming	Command Class Powerlevel
Command Class Protection	Command Class Scene Activation
Command Class Scene Actuator Conf	Command Class Security 2
Command Class Supervision	Command Class Switch Binary
Command Class Transport Service V2	Command Class Version V2
Command Class Z-Wave+ Info V2	

**Controlled Command Classes (1):**

Command Class Basic V2
------------------------