



Z-Wave Protocol Implementation Conformance Statement

Eaton's Z-Wave Plus Wireless Switch

General Information

Product Identifier:	RF9601
Brand Name:	Eaton
Product Version:	HW: 255 FW: 2.00
Z-Wave Certification #:	ZC10-18096234

Product Features

Switch Type	Decorator Paddle Push with Indicator
Firmware Updatable	Updatable by Consumer by RF
Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Neutral Wire Required	Yes
Switch Load Capacity Current	15A
Z-Wave Scene Type	Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Eaton’s Z-Wave Plus Wireless Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0503
Z-Wave Product Type:	0x534C
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave, No FLiRS, No MR
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline
2 / 5	ON/OFF

Supported Command Classes (19):

Alarm	Association Group Info
Association V2	Basic V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Node Naming	Powerlevel
Protection	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2
