

Z-Wave Protocol Implementation Conformance Statement

Eatons Z-Wave Plus Wireless Receptacle

General Information

Product Identifier:	RFTR9605-T
Brand Name:	Eaton
Product Version:	HW: 0 FW: 2.00
Z-Wave Certification #:	ZC10-18096232

Product Features

Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15A
Neutral Wire Required	Yes
Switch Type	Push Button with Indicator
Z-Wave Scene Type	Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Eatons Z-Wave Plus Wireless Receptacle

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0505
Z-Wave Product Type:	0x5244
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave, No FLiRS, No MR
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 5	ON/OFF

Supported Command Classes (19):

Alarm	Association Group Info
Association V2	Basic V2
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Node Naming	Powerlevel
Protection	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2
