

## Z-Wave Protocol Implementation Conformance Statement

### 2 Scene Z-Wave controller

#### General Information

<b>Product Identifier:</b>	34174/ZW5305
<b>Brand Name:</b>	GE
<b>Product Version:</b>	HW: 255 FW: 5.08
<b>Z-Wave Certification #:</b>	ZC10-18096224

#### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	CR2032
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Manufacturer

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3033
<b>Z-Wave Product Type:</b>	0x4843
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Portable Controller
<b>Z-Wave Device Type / Role Type:</b>	Remote Control - Multi Purpose / Portable Controller

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 2 Scene Z-Wave controller

### Supported Command Classes (9):

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Version V2	Wake Up V2
Z-Wave Plus Info V2	

### Controlled Command Classes (3):

Basic	Switch Multilevel
Wake Up V2	