

Z-Wave Protocol Implementation Conformance Statement

Smart Boost Timer Switch

General Information

Product Identifier:	ZWA006-C
Brand Name:	Aeotec
Product Version:	HW: 2 FW: 1.00:01.00
Z-Wave Certification #:	ZC10-18106255

Product Features

Switch Type	Push Button
Switch Load Capacity Current	16A
Supported Meter Type	Electric Energy
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Volt-Ampere	220V 16A
Battery Quantity	1
Battery Type	CR2032
Color	White
Sensors	Power
Switch Load Capacity Watts	3680W
Electric Load Type	Incandescent
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Boost Timer Switch

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x00B4
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 COMMAND_CLASS_SWITCH_BINARY/SWITCH_BINARY_REPORT
COMMAND_CLASS_METER_V5/METER_REPORT_V5
COMMAND_CLASS_CLOCK/CLOCK_REPORT
COMMAND_CLASS_SENSOR_MULTILEVEL_V11/SENSOR_MULTILEVEL_REPORT_V11
COMMAND_CLASS_SCHEDULE/SCHEDULE_STATE_REPORT
COMMAND_CLASS_DEVICE_RESET_LOCALLY/DEVICE_RESET_LOCALLY_NOTIFICATION

Supported Command Classes (20):

3ET

Association Group Info	Association V2
Basic V2	Clock
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V5	Multi-Channel Association V3
Powerlevel	Schedule
Security S0	Security S2
Sensor Multilevel V11	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2