

Z-Wave Protocol Implementation Conformance Statement

Siren

General Information

Product Identifier:	NAS-AB02ZE
Brand Name:	Coolcam
Product Version:	HW: 96 FW: 2.17
Z-Wave Certification #:	ZC10-18096227

Product Features

Battery Quantity	2
Communications Connections	None
Gateway Has Preferred Partners	No
Sensors	Open/Closed (Binary)
Supported Notification Types	Home Security Siren
Battery Type	CR123A
Color	White
Firmware Updatable	Updatable by Professional/Technician

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Siren

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1028
Z-Wave Product Type:	0x0200
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Siren / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline Command Class COMMAND_CLASS_NOTIFICATION
COMMAND_CLASS_SWITCH_BINARY COMMAND_CLASS_BATTERY
COMMAND_CLASS_DEVICE_RESET_LOCALLY Event NOTIFICATION_REPORT

Supported Command Classes (17):

RY_REPORT DEVICE_RESET_LOCALLY_NOTIFICATION

Association Group Info	Association V2
Basic V2	Battery
Configuration	Device Reset Locally
Indicator	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Supervision	Switch Binary
Transport Service V2	Version V3
Z-Wave Plus Info V2	