



Z-Wave Protocol Implementation Conformance Statement

Voice Siren

General Information

Product Identifier:	SE813-2
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.02:00.01
Z-Wave Certification #:	ZC10-18096241

Product Features

Color	White
Battery Quantity	4
Supported Notification Types	Siren
Sensors	Air Temperature
Battery Type	LR14
Firmware Updatable	Updatable by Consumer via Internet

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Voice Siren

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0003
Z-Wave Product Type:	0x000C
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Siren / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (19):

Command Class Association Group Info	Command Class Association V2
Command Class Basic	Command Class Battery
Command Class Configuration	Command Class Device Reset Locally
Command Class Firmware Update Md V4	Command Class Manufacturer Specific V2
Command Class Notification V8	Command Class Powerlevel
Command Class Security	Command Class Security 2
Command Class Sensor Multilevel V5	Command Class Sound Switch
Command Class Supervision	Command Class Switch Binary
Command Class Transport Service V2	Command Class Version V3
Command Class Z-Wave+ Info V2	