

Z-Wave Protocol Implementation Conformance Statement

Samsung Galaxy Home

General Information

| | |
|--------------------------------|--------------------------------|
| Product Identifier: | SM-V510 |
| Brand Name: | Samsung Electronics, Co., Ltd. |
| Product Version: | HW: 38 FW: 5.03:00.22 |
| Z-Wave Certification #: | ZC10-18116290 |

Product Features

| | |
|---|--|
| Supported Notification Types | Smoke Alarm Water Alarm |
| Communications Connections | Ethernet (Wireless/WiFi) |
| Controller Supports Multiple Z-Wave Interfaces | No |
| Controller Supports Multiple Networks | No |
| Firmware Updatable | Updatable by Consumer by Wire |
| Z-Wave Scene Type | Central Scene |
| Gateway Has Preferred Partners | Yes |
| Sensors | Air Temperature Humidity Luminance |
| Color | Navy Blue |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Samsung Galaxy Home

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0026 |
| Z-Wave Product Type: | 0x0008 |
| Z-Wave Hardware Platform: | SD3503 |
| Z-Wave Development Kit Version: | 6.71.03 |
| Z-Wave Library Type: | Static Controller |
| Z-Wave Device Type / Role Type: | Central Controller / Central Static Controller |

Association Group Information

Group # / Max Description

Nodes

1 / 4 Z-Wave Plus Lifeline

Supported Command Classes (11):

| | |
|----------------------|--------------------------|
| Application Status | Association Group Info |
| Association V2 | CRC16 Encapsulation |
| Device Reset Locally | Manufacturer Specific V2 |
| No Operation | Powerlevel |
| Security S0 | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (28):

| | |
|------------------------|-------------------------------|
| Association Group Info | Association V2 |
| Barrier Operator | Basic |
| Battery | Configuration V2 |
| CRC16 Encapsulation | Device Reset Locally |
| Door Lock V2 | Manufacturer Specific V2 |
| Meter V3 | Multi-Channel Association V3 |
| Multi-Channel V4 | Notification V5 |
| Security S0 | Sensor Binary V2 |
| Sensor Multilevel V5 | Switch Binary |
| Switch Color V2 | Switch Multilevel V3 |
| Thermostat Fan Mode V3 | Thermostat Fan State V2 |
| Thermostat Mode V2 | Thermostat Operating State V2 |
| Thermostat Setpoint V2 | Version V2 |
| Wake Up V2 | Z-Wave Plus Info V2 |