

## Z-Wave Protocol Implementation Conformance Statement

### SONATA 1

#### General Information

<b>Product Identifier:</b>	0000/4790
<b>Brand Name:</b>	TechniSat
<b>Product Version:</b>	HW: 3 FW: 4.61:02.27:01.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-18106260

#### Product Features

<b>Communications Connections</b>	Bluetooth Ethernet (Wired) Ethernet (Wireless/WiFi) HDMI (High-Definition Multimedia Interface) USB (Universal Serial Bus)
<b>Sensors</b>	Air Temperature Humidity Luminance Motion/No Motion (Binary) Open/Closed (Binary) Ultraviolet Index
<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	Home Security
<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Firmware Updatable</b>	Updatable by Consumer via Internet

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## SONATA 1

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1838
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 1                    Z-Wave Plus Lifeline

#### Supported Command Classes (22):

Application Status	Association Group Info
Association Group Information V3	Association V2
CRC16 Encapsulation	Device Reset Locally
Mailbox	Manufacturer Specific V2
Multi-Command	Network Management Basic
Network Management Inclusion	Network Management Installation and Maintenance
Network Management Proxy	Powerlevel
Security S0	Transport Service V2
Version V2	Z/IP Gateway
Z/IP Naming and Location	Z/IP Portal
Z/IP V3	Z-Wave Plus Info V2

#### Controlled Command Classes (25):

Association Group Info	Association Group Information V3
Association V2	Basic
Battery	Configuration
CRC16 Encapsulation	Manufacturer Specific V2
Meter V3	Multi-Channel Association V3
Multi-Channel V4	Network Management Basic
Network Management Inclusion	Network Management Proxy
Notification V3	Powerlevel
Security S0	Sensor Binary V2
Sensor Multilevel V6	Switch Binary
Thermostat Setpoint	Transport Service V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	