

## Z-Wave Protocol Implementation Conformance Statement

### Vivint Smart Hub

#### General Information

<b>Product Identifier:</b>	CP04
<b>Brand Name:</b>	Vivint
<b>Product Version:</b>	HW: 1 FW: 6.01:02.81:01.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-18106282

#### Product Features

<b>Sensors</b>	Air Temperature
<b>Supported Notification Types</b>	Home Security
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Communications Connections</b>	Ethernet (Wired) Ethernet (Wireless/WiFi)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

Vivint Smart Hub

## Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 232            Z-Wave Plus Lifeline

**Supported Command Classes (14):**

Association Group Info	Association V2
CRC16 Encapsulation	Device Reset Locally
Inclusion Controller	Manufacturer Specific
No Operation	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (31):**

Anti-Theft V2	Association V2
Barrier Operator	Basic
Battery	Clock
Configuration	CRC16 Encapsulation
Door Lock V2	Firmware Update Meta-Data V3
Indicator	Manufacturer Specific
Multi-Channel Association V3	Multi-Channel V4
No Operation	Notification V8
Powerlevel	Security S0
Security S2	Sensor Multilevel
Switch Binary	Switch Multilevel
Thermostat Fan Mode	Thermostat Fan State
Thermostat Mode	Thermostat Operating State
Thermostat Setpoint	User Code
Version V2	Wake Up V2
Z-Wave Plus Info V2	