

## Z-Wave Protocol Implementation Conformance Statement

### Mini plug with metering

#### General Information

<b>Product Identifier:</b>	AN184-1
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.00:00.04
<b>Z-Wave Certification #:</b>	ZC10-18106278

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x000B
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Mini plug with metering

2 / 4

On/Off Control

### Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V3	Notification V4
Powerlevel	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic