

Z-Wave Protocol Implementation Conformance Statement

S2 Dimmer

General Information

Product Identifier:	ZEN27
Brand Name:	Zooz
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-18116309

Product Features

Electric Load Type	Dimmable LED Incandescent LED
Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Watts	300 W (incandescent with all heat sink tabs on) / 100 W LED's
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xA002
Z-Wave Product Type:	0xA000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

S2 Dimmer

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Z-Wave Plus Lifeline

2 / 5 This device will send MULTILEVEL REPORT to Group 1 and 2 when operated manually.

Supported Command Classes (15):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2