

## Z-Wave Protocol Implementation Conformance Statement

### 5-Outlet Power Strip

#### General Information

|                                |                |
|--------------------------------|----------------|
| <b>Product Identifier:</b>     | ZEN20 VER. 2.0 |
| <b>Brand Name:</b>             | Zooz           |
| <b>Product Version:</b>        | HW: 1 FW: 1.00 |
| <b>Z-Wave Certification #:</b> | ZC10-18116311  |

#### Product Features

|                                     |                                |
|-------------------------------------|--------------------------------|
| <b>Supported Meter Type</b>         | Electric Energy                |
| <b>Supported Notification Types</b> | Power Management               |
| <b>Electric Load Type</b>           | Incandescent<br>LED            |
| <b>Firmware Updatable</b>           | Updatable by Consumer by RF    |
| <b>Switch Load Capacity Current</b> | 15 A (total between 5 outlets) |
| <b>Color</b>                        | White                          |

#### Z-Wave Product Information

|                                      |                         |
|--------------------------------------|-------------------------|
| Supports Z-Wave Beaming Technology?  | Yes                     |
| Supports Z-Wave Network Security?    | Yes                     |
| Supports Z-Wave AES-128 Security S0? | No                      |
| Supports Security S2?                | Yes: S2 Unauthenticated |
| SmartStart Compatible?               | No                      |

#### Z-Wave Technical Information

|  |                        |
|--|------------------------|
| <b>Z-Wave Frequency:</b>               | U.S. / Canada / Mexico |
| <b>Z-Wave Product ID:</b>              | 0xA004                 |
| <b>Z-Wave Product Type:</b>            | 0xA000                 |
| <b>Z-Wave Hardware Platform:</b>       | ZM5202                 |
| <b>Z-Wave Development Kit Version:</b> | 6.71.03                |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 5-Outlet Power Strip

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                    Z-Wave Plus Lifeline

**Supported Command Classes (18):**

|                              |                              |
|------------------------------|------------------------------|
| Association Group Info       | Association V2               |
| Basic V2                     | Configuration                |
| Device Reset Locally         | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2     | Meter V4                     |
| Multi-Channel Association V3 | Multi-Channel V4             |
| Notification V8              | Powerlevel                   |
| Security S2                  | Supervision                  |
| Switch Binary                | Transport Service V2         |
| Version V3                   | Z-Wave Plus Info V2          |

**Controlled Command Classes (1):**

Basic V2