



Z-Wave Protocol Implementation Conformance Statement

Smart Dimmer Plug

General Information

Product Identifier: PAD09-3
Brand Name: Philio Technology
Product Version: HW: 1 FW: 1.01
Z-Wave Certification #: ZC10-18126331

Product Features

Supported Notification Types Power Management
Firmware Updatable Updatable by Manufacturer

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x0060
Z-Wave Product Type: 0x0005
Z-Wave Hardware Platform: SD3502
Z-Wave Development Kit Version: 6.81.01
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 5	Group 1 name:Lifename Group 1 command list: COMMAND_CLASS_SWITCH_MULTILEVEL_V2, COMMAND_CLASS_NOTIFICATION_V8, COMMAND_CLASS_DEVICE_RESET_LOCALLY

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Dimmer Plug

2 / 5 Group 2 name:Control Key1 Group 2 command list: COMMAND_CLASS_BASIC_SET,

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V8
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Multilevel V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic