

Z-Wave Protocol Implementation Conformance Statement

Smart Plug

General Information

Product Identifier:	HKZW-SO08 P
Brand Name:	Hank
Product Version:	HW: 1 FW: 1.02
Z-Wave Certification #:	ZC10-19016348

Product Features

Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer via Internet
Supported Meter Type	Electric Energy
Switch Load Capacity Current	10A
Switch Load Capacity Volt-Ampere	230V
Switch Load Capacity Watts	2300W
Switch Type	Push Button Illuminated
Color	White
Communications Protocol	Z-Wave Serial API

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0019
Z-Wave Product Type:	0x0100
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2