

## Z-Wave Protocol Implementation Conformance Statement

### Digital Door Lock

#### General Information

<b>Product Identifier:</b>	YDM3109+
<b>Brand Name:</b>	Yale
<b>Product Version:</b>	HW: 32 FW: 33.17:13.16
<b>Z-Wave Certification #:</b>	ZC10-19036386

#### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	AA
<b>Color</b>	Black
<b>Communications Connections</b>	Bluetooth Manufacturer Proprietary
<b>Door Lock Type</b>	Lever Handle
<b>Gateway Has Preferred Partners</b>	Yes
<b>Supported Notification Types</b>	Access Control Emergency Alarm Home Security Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Digital Door Lock

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x0300
<b>Z-Wave Product Type:</b>	0xC600
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                Z-Wave Plus Lifeline

**Supported Command Classes (19):**

Alarm	Association Group Info
Association V2	Battery
Device Reset Locally	Door Lock Logging
Door Lock V2	Manufacturer Specific V2
Powerlevel	Schedule Entry Lock V3
Security S0	Security S2
Supervision	Time Parameters
Time V2	Transport Service V2
User Code	Version V2
Z-Wave Plus Info V2	