

Z-Wave Protocol Implementation Conformance Statement

1 Touch Panel Switch

General Information

Product Identifier:	HTP-1S0
Brand Name:	Hogar Controls
Product Version:	HW: 255 FW: 2.50
Z-Wave Certification #:	ZC10-19046451

Product Features

Switch Load Capacity Current	3
Switch Load Capacity Watts	700
Neutral Wire Required	Yes
Firmware Updatable	Updatable by Professional/Technician
Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

1 Touch Panel Switch

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x4411
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5	Name: Lifeline Command: - Device Reset Locally Notification - Switch Binary Report
2 / 5	Name: HGT-01 Command: - Basic Set Device support control another device through root device association group #2~#3, and each group support 5 destination nodes maximum.
3 / 5	Name: HGT-01 Command: - Switch Binary Set Device support control another device through root device association group #2~#3, and each group support 5 destination nodes maximum.

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic	Switch Binary
-------	---------------