

Z-Wave Protocol Implementation Conformance Statement

Shutter Control

General Information

Product Identifier:	SCM-2ZW
Brand Name:	Climax Technology
Product Version:	HW: 255 FW: 4.01
Z-Wave Certification #:	ZC10-19036397

Product Features

Firmware Updatable	Updatable by Consumer by RF
Window Covering Control Features	Supports Up/Down Motion

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0005
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering - Pos/End Aware / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	Z-Wave Plus Lifeline Switch MultilevelCC,V4 (COMMAND_CLASS_SWITCH_MULTILEVEL) Device Reset Locally CC, V4 (COMMAND_CLASS_DEVICE_RESET_LOCALLY) When SCM changes its position:

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Shutter Control

Supported Command Classes (16):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Binary
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2