

## Z-Wave Protocol Implementation Conformance Statement

# Roller Shutter Multi Level Switch

### General Information

<b>Product Identifier:</b>	Roller Shutter/TD11000Z2
<b>Brand Name:</b>	Good Way Technology, Co., Ltd
<b>Product Version:</b>	HW: 1 FW: 2.00
<b>Z-Wave Certification #:</b>	ZC10-19036390

### Product Features

<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Supported Meter Type</b>	Electric Energy
<b>Window Covering Control Features</b>	Supports Curtains Supports Rotation Motion Supports Up/Down Motion Supports Vertical Blinds

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0014
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Window Covering - Pos/End Aware / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Roller Shutter Multi Level Switch

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    Z-Wave Plus Lifeline

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Powerlevel	Security S0
Security S2	Supervision
Switch Binary	Switch Multilevel V3
Transport Service V2	Version V2
Z-Wave Plus Info V2	