



Z-Wave Protocol Implementation Conformance Statement

Danalock V3-BTZU

General Information

Product Identifier: Danalock V3-BTZU
Brand Name: Danalock
Product Version: HW: 2 FW: 1.03:00.10
Z-Wave Certification #: ZC10-19046418

Product Features

Supported Notification Types Access Control
Battery Quantity 4
Battery Type CR123
Firmware Updatable Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Access Control
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x0001
Z-Wave Product Type: 0x0009
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.71.03
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Door Lock - Keypad / Listening Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Danalock V3-BTZU

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Z-Wave Plus Lifeline • Device Reset Locally: triggered upon reset. • Battery/notification: triggered upon low battery. • Door Lock operation report: triggered upon a change in door lock • Notification: triggered upon a change in door lock

Supported Command Classes (20):

Command Class Association Group Info	Command Class Association V2
Command Class Battery	Command Class Configuration
Command Class Device Reset Locally	Command Class Door Lock V2
Command Class Firmware Update Md V4	Command Class Manufacturer Specific V2
Command Class Notification V8	Command Class Powerlevel
Command Class Schedule Entry Lock V3	Command Class Security
Command Class Security 2	Command Class Supervision
Command Class Time	Command Class Time Parameters
Command Class Transport Service V2	Command Class User Code
Command Class Version V2	Command Class Z-Wave+ Info V2