

Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Dimmer

General Information

Product Identifier:	14294/46203/ZW3010
Brand Name:	GE
Product Version:	HW: 255 FW: 5.53
Z-Wave Certification #:	ZC10-19046444

Product Features

Neutral Wire Required	Yes
Z-Wave Scene Type	Central Scene
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3235
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.04
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Dimmer

- 2 / 5 Supports Basic Set and is controlled by pressing the ON or OFF button with the local load
- 3 / 5 Supports Basic Set and is controlled by double pressing the ON or OFF button

Supported Command Classes (16):

- | | |
|--------------------------|------------------------------|
| Application Status | Association Group Info |
| Association V2 | Basic V2 |
| Central Scene V3 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Powerlevel |
| Security S2 | Supervision |
| Switch Multilevel V4 | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

- Basic V2