

## Z-Wave Protocol Implementation Conformance Statement

# Smart Humidity And Temperature Sensor

### General Information

**Product Identifier:** 51112  
**Brand Name:** CLEVERIO  
**Product Version:** HW: 255 FW: 3.01  
**Z-Wave Certification #:** ZC10-19056481

### Product Features

**Battery Type** CR2450  
**Color** White  
**Sensors** Air Temperature  
Humidity  
**Battery Quantity** 1

### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? Yes: S2 Unauthenticated  
SmartStart Compatible? No

### Z-Wave Technical Information

**Z-Wave Frequency:** CEPT (Europe)  
**Z-Wave Product ID:** 0x1000  
**Z-Wave Product Type:** 0x8007  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.71.03  
**Z-Wave Library Type:** Routing Slave  
**Z-Wave Device Type / Role Type:** Notification Sensor / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Humidity And Temperature Sensor

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    - Lifeline between controller and the product - Supported command classes: Battery Report, Multilevel Sensor Report, and Device Reset Locally notification. - Association Group description Association group 1: Lifeline association group Maximum supported node is 5 Include command classes: Battery report, multilevel sensor report, and Device Reset Locally

**Supported Command Classes (14):**

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Sensor Multilevel V10	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2