

Z-Wave Protocol Implementation Conformance Statement

Outdoor Smart Plug - 1 channel

General Information

Product Identifier:	ZW96
Brand Name:	EVA LOGIK
Product Version:	HW: 255 FW: 1.255
Z-Wave Certification #:	ZC10-19056511

Product Features

Electric Load Type	Incandescent Inductive (e.g. Motor) LED
Color	Black
Switch Load Capacity Watts	1800W
Switch Type	Toggle
Firmware Updatable	Updatable by Manufacturer
Outdoor Use	Yes
Supported Notification Types	Heat Alarm
Switch Load Capacity Volt-Ampere	16A

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Outdoor Smart Plug - 1 channel

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xC003
Z-Wave Product Type:	0xC000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline
2 / 5 basic set command

Supported Command Classes (17):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2